

## CON-1

### Circuit Continuity Indicator

The CON-1 is a mini Blaster's Ohmmeter that indicates a complete circuit and its detected level of resistance to the user by LED indications.

#### CON-1 Features and Benefits:

- Low power consumption
- Compact design
- Allows for quick connection and release of lead lines
- Multiple measure range



### Technical characteristics

Parameter	Value
Measuring range	0-50 $\Omega$ , 51-200 $\Omega$ , 201-400 $\Omega$
Measuring accuracy	+/-2 $\Omega$
Maximum measuring current	1.5mA
On State	Immediate when circuit present on contacts
Power supply	3V CR2032
Protection level of outer casing (per IEC 60529)	IP67
Operating temperature	-30 to +65 $^{\circ}\text{C}$
Dimensions	72 x 43 x 15.5 mm
Weight	32 g